



DX-1 Power / Signal Manager



www.qanon-audio.com



DX-1 Power / Signal Manager

DX-1

DX-1 use single-phase power supply, can be compatible with C15 rack power supply support. The main power interface use 10² wires, and each internal channel adopts 6² wires. At the same time, it can drive 6 x C15 and 6 x H series power amplifier controllers.

2U distribution of front panel includes 4 x XLR3 inputs, 1 x 32A 3-pin power input interface, 8 x Neutrik® NL4 speaker cable connector output, 100A main power switch and 1 channel led voltage display. The rear panel has 4 XLR3 outputs, 1 x 32A 3-pin power output interface, 6 channel powerCON 20A power output, and 2 channel power socket.

Technical Specification

Front connectors

Main power Input	AC~220V 32A 3-Pin(L+N+G)
Analog Input	4 x female Neutrik® XLR3 (IN)
SpeakOn NL4 Output	8 x Neutrik® NL4
AC Voltage Panel display	1 channel Display
Power channel	8-channel power supply sequence
Power switch	100A
Forced start	PASS
Switch	ON/OFF

Rear connectors

Main power Output	AC~220V 32A 3-Pin(L+N+G)
Analog Output	4 x male Neutrik® XLR3(OUT)
SpeakOn NL4 Input	8 x Neutrik® NL4
power supply	6 x 20A
Auxiliary power supply	2 x power outlets

Physical data

Dimensions (W x H x D)	483 x 88 x 460 mm
Material	Metal
Finish	Black
Protection rating	IP2x
Weight	11kg / 24.2lb

DX-1 Dimensions CAD

